



Appreciating Quality Automation

We at "DOLPHIN AUTOMATION" thank you for the purchase of this product and we assure you for our best services.....always!

PROGRAMMABLE TIMER

MODEL NO:-T-361/T661

SPECIFICATIONS

SET TIME (RANGE)	:	(HH.MM.SS.) (MM.SS.MS.) (OPTIONAL)
SET TIME (RANGE)	:	(HH.MM.SS.) (MM.SS.MS.) (OPTIONAL)
SET POINT (ON TIME RANGE)	:	(HH.MM.SS.) (MM.SS.MS.) (OPTIONAL)
SET POINT (OFF TIME RANGE)	:	(HH.MM.SS.) (MM.SS.MS.) (OPTIONAL)
RESET	:	Both front & Remote Reset
OUT PUT	:	5 A @ 230 VAC
	:	SPDT RELAY
POWER	:	AC 220 V+/- 10% @ 50Hz
	:	24 VAC /DC modes-on Request
OPERATING TEMP	:	0-50 deg C

PROGRAMMING / OPERATING ISTRUCTIONS

- 1- To view/change RELAY ON TIME press SELECT KEY once.
- 2- To view/change RELAY ON TIME press SELECT KEY twice.
- 3- To set ON/ OFF Time set value. Press select key to select on /off Time value and press UP/DOWN key to change the current set value. Also use select key to change Hour/Minute /Second /Mill Second mode after pressing UP/DOWN KEY once.(Range 00.00.00/59.59).
- 4- Press select key continuously for Storing the current new value till STORE displayed.
- 5- RESET (Front & Back RESET mode available).
 - A- Front Reset Mode- Front Panel Reset key is used to reset & Stop timer. Press again the same key to Start Tim.
 - B- Back Reset Mode (1) Back Panel Reset key is used to Clear & Restart Time.
 - C- Back Reset Mode (2) Target/ Switch OFF to ON reset & Start or ON to OFF Reset & Start (optional)

PROGRAMMING THE TIMER

